

PROCEDURE FOR ENSURING THE OPERATION OF SIGNALLING CHANNELS IN A V5 INTERFACE

This application is a continuation of international appli-
cation number PCT/IF98/00198, filed Mar. 5, 1998, pend-
ing.

FIELD OF THE INVENTION

The present invention relates to a procedure for ensuring
the operation of protected signalling channels in a V5
interface between a local exchange and an access node in
conjunction with a redefinition of the composition of the
interface.

DESCRIPTION OF RELATED ART

Open interfaces (V5.1 and V5.2) between an access node
and a local exchange are defined in the ETSI (European
Telecommunications and Standards Institute) standards of
the ETS 300 324 and ETS 300 347 series. V5 interfaces
enable subscribers belonging to a physically separate local
network to be connected to a telephone exchange using a
standard interface. In the present application, V5 interface
expressly refers to a dynamic concentrator interface (V5.2)
as defined in the ETS 300 347 standard series, consisting of
one or more (1-16) PCM (Pulse Code Modulation) cables.
One PCM cable comprises 32 channels, each of which with
a transfer rate of 64 kbit/s, i.e. 2048 kbit/s in all. The V5.2
interface supports analogue telephones as used in the public
telephone network, digital, such as ISDN (Integrated Ser-
vices Digital Network) basic and system subscriber connec-
tions as well as other analogue or digital terminal equipment
based on semi-fixed connections.

Certain time slots in the V5 interface, which form a
channel called C-channel, serve to transmit the protocols
used for controlling the interface itself and the calls trans-
mitted over the interface. A C-channel or a 64 kbit/s time slot
reserved for this purpose serves to transmit information that
may belong e.g. to the Control protocol, Link control
protocol, Protection protocol or BCC protocol of the V5
interface, or which may consist of PSTN signalling or ISDN
data. Further, according to the standards mentioned above, a
C-channel can be reserved for time slots 16, 15 and/or 31 in
the PCM line or V5 interface link. Especially in a V5.2
interface, the system automatically creates C-channels for
the critical protocols (Control, Link control, BCC and
Protection), whereas the operator can place the PSTN sig-
nalling as desired, either in the same channel with the critical
protocols or in another C-channel. In addition, the operator
may allocate a maximum of three signalling channels as
so-called backup channels. These channels are resorted to in
the case of a failure of the link to which the channels were
originally allocated. In a V5.2 interface having more than
one 2-Mbit/s link, a link whose physical C-channel in time
slot 16 transmits the Control, Link control, BCC and Pro-
tection protocols is defined as the primary link. Further, a
link whose physical C-channel in time slot 16 only transmits
the Protection protocol is a secondary link.

The above-mentioned standards define two different ways
of changing the data for a V5 interface already activated.
Changing the data means e.g. that a signalling channel is
transferred to another time slot or that additional signalling
channels are introduced. Such changes can be effected using
the so-called reprovision function defined in the standard,
in which case the altered data are given a new "designation"
(provision variant) at both ends, i.e. in the local exchange

and in the access node. The provision variant is a parameter
which is checked in conjunction with the start-up of the V5
interface. This verification serves to ensure that both the
local exchange and the access node observe the same
composition in the V5 interface. Composition means in the
first place the locations and order of the signalling channels.
When the parameter in question is assigned a new value, this
means that e.g. the signalling channels have a new location.
When the changes are activated at both ends, i.e. when the
interface is started up, the hardware first ensures via signal-
ling that the new value of the "provision variant" is known
at both ends, whereupon the changes of composition or
configuration are made independently according to the
parameter in question. However, it is also possible to make
changes in the V5 interface without using the reprovision
function. In this case, the changes are made independently at
both ends without altering the value of the provision variant
parameter. When the changes are activated, the defined
changes are made automatically at both ends and the inter-
face is started up.

The locations of the signalling channels in an active
interface may change in consequence of a protection switch-
over of a signalling channel. This creates a situation where
the interface configuration is no longer consistent with the
configuration originally defined by the operator. The prob-
lem is that the above-mentioned standards do not define
whether the possible protection switch-over cases should be
taken into account or not when a new configuration or
composition is introduced. Further, when the composition of
the interface is being defined, it must also be taken into
account that one of the links may have been damaged and
that consequently the signalling channels transmitted via
that link are switched over to another link. FIGS. 1a and 1b
present an example of such a situation. FIG. 1a illustrates
normal operation between a local exchange LE and an
access node AN. In this V5 interface, the signalling channel,
which may be e.g. the BCC protocol, has been allocated to
the topmost link in the V5 interface. Further, a backup
channel has been allocated to the bottom most link in the
interface. FIG. 1b illustrates an example situation where the
backup channel and signalling channel are swapped, i.e. the
signalling channel is switched over to the backup channel
when the link is damaged.

SUMMARY OF THE INVENTION

The object of the present invention is to eliminate the
problems described above. A specific object of the present
invention is to present a new procedure that makes it
possible to flexibly ensure the activation of the signalling
channels in a V5 interface when a new composition is
defined for the V5 interface without the reprovision func-
tion.

In the procedure of the invention, in a V5 interface
between a local exchange and an access node, said interface
comprising at least two links, to ensure the operation of the
signalling channels in conjunction with a redefinition of the
interface composition, in which redefinition changes are
made in the V5 interface data, such as the placement of
signalling channels on the links, according to the invention,
the operation of protected channels is ensured in conjunction
with restarting by activating the protected channels on the
channels defined for them in the new composition and/or on
the channels to which they were transferred in conjunction
with the protection switch-over. The redefinition of the V5
interface composition is preferably carried out indepen-
dently both in the local exchange and in the access node
without changing the value of the interface composition
parameter.